

ACCESS SERVICE

	<u>Page</u>	
30. <u>OC-192 Dedicated SONET Ring Service</u>	30-2	
30.1 General Description	30-2	
(A) Basic Service Description	30-2	
(B) Service Provisioning	30-3	
(C) Responsibility of The Telephone Company	30-4	
(D) Rights of The Telephone Company	30-4	
(E) Responsibility of Customer	30-4	
30.2 Technical Specifications	30-5	
30.3 Rate Regulations	30-5	
(A) Rate Elements	30-5	
(B) Dedicated Ring Connection Capacity	30-8	
(C) Term Pricing Plan	30-9	
(D) Moves	30-11	
(E) Upgrade to OC-192 Dedicated SONET Ring Service from Lower Speed Services	30-12	
(F) Migration onto OC-192 Dedicated SONET Ring	30-12	
(G) Shared Network Arrangement	30-13	
(H) Shared Use	30-13	
(I) Optical-to-Electrical DS3 Add/Drop Capability	30-13.1	
(J) Upgrade to Next Generation SONET equipment (required for Ethernet ports)	30-13.2	
(K) Re-Map Service	30-13.2	
(L) STS-1 Service	30-13.3	(N)
30.4 Rates and Charges	30-14	
(A) Node	30-14	
(B) Add/Drop Capability	30-14	
(C) Ports	30-14	
(D) Mileage	30-16	
(E) Ring Regenerator	30-16	
(F) Shared Network Arrangement	30-16	
(G) Installation and Rearrangement Charges	30-16	
(H) Optical-to-Electrical Add/Drop Capability	30-17	(N)

(This page filed under Transmittal No. 3168)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service30.1 General Description(A) Basic Service Description

OC-192 Dedicated SONET Ring Service is a 9.953 Gbps transport service. OC-192 is designed for transport of lower speed services, e.g. DS3, OC-3 or OC-3c, OC-12 or OC-12c, OC-48 or OC-48c, OC-192, 100 Mbps Ethernet or 1 Gbps Ethernet. The dedicated ring is designed to provide increased reliability and functionality by connecting multiple customer locations and specified Telephone Company Central offices via self-healing Rings. OC-192 is a logical extension of the existing SONET products OC-3, OC-3c, OC-12, OC-12c, OC-48 and OC48c.

The dedicated ring can connect multiple (between 2 and 16) customer-designated locations and telephone company central offices, as described in Section 30.1(B)(1) following, where SONET facilities and equipment are available.

Rate elements include nodes, ports, mileage, regenerators, and add/drop capability. Rates are specified in 30.4 following.

Rates and charges for OC-192 Dedicated SONET Ring Service are set forth in Section 30.4, following, with the exception of the services provided by the Telephone Company in the Metropolitan Statistical Areas (MSAs) in which the Telephone Company has received Phase II pricing flexibility pursuant to Subpart H of Part 69 of the Commission's Rules. The rates and charges for the OC-192 Dedicated SONET Ring Service in the MSAs that have received Phase II pricing flexibility are set forth in Section 39.

(N)

(N)

(This page filed under Transmittal No. 3120)

Issued: March 3, 2006

Effective: March 18, 2006

One SBC Plaza, Dallas, Texas 75202

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)

(N)

30.1 General Description (Cont'd)(B) Service Provisioning(1) Manner of Provisioning

All customers will be served from the nearest suitably equipped end office. Information pertaining to end offices equipped to provide OC-192 Dedicated SONET Ring Service is set forth in the National Exchange Carrier Association, Inc. (NECA) Tariff F.C.C. No. 4. OC-192 Dedicated SONET Ring Service will be provided subject to the availability and limitations of The Telephone Company's wire centers and outside plant facilities. OC-192 Dedicated SONET Ring Service is only available where technical capabilities permit such facility distance and type of physical plant. Where facilities are not available, Special Construction charges may apply.

(2) Limitations

The Telephone Company does not undertake to originate data, but offers the use of its OC-192 Dedicated SONET Ring Service, where available, to customers for the purpose of transporting data originated by the customer or a third party.

Unprotected services may be interrupted to repair other circuits. In cases where the customer orders OC-192 Dedicated SONET Ring Service with an unprotected 2-fiber service interface, the Telephone Company may provision this unprotected service, with other unprotected services, via a multi-port circuit card. If one unprotected service on the card incurs an outage, the Telephone Company may repair the 2-fiber service interface device by replacing the card, which may temporarily interrupt service on any other unprotected tributary circuits that subtend this same multi-port circuit card. In the event of a service interruption, credit allowance will be provided for the service that suffered the unplanned outage, as outlined in Section 30.1(B)(3), following.

The Telephone Company will maintain and repair the OC-192 Ring Service which it furnishes and will provide the customer reasonable notification of service affecting activities that may occur in the normal operation of business.

(N)

(This page filed under Transmittal No. 2847)

Issued: November 1, 2000

Effective: November 2, 2000

One Bell Plaza, Dallas, Texas 75202

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)

(N)

30.1 General Description (Cont'd)(B) Service Provisioning (Cont'd)(3) Allowance for Service Interruptions

Dedicated Rings provide Automatic Protection Switching to assure 100 percent availability of the services on the ring. A service interruption will result in a credit equal to one month's bill for the individual port-to-port connection involved. An interruption of service will start when an inoperative service is reported to the Telephone Company and end when the service is operative. In any month, as a result of an interruption, the total credit per rate element of the interrupted service may not exceed 100 percent of the monthly charge for that particular rate element.

In the event that protected facilities do not exist, including dual entrance facilities, and the customer does not utilize Special Construction to provide protected facilities, the unprotected OC-192 ring will be provided. The SONET Assurance Warranty states that if any unavailability caused by the Telephone Company is experienced and reported by a customer, the Telephone Company will rebate the service monthly recurring charge.

(C) Responsibility of The Telephone Company

The Telephone Company will provision and maintain OC-192 Dedicated SONET Ring Service for the customer up to and including the Network Interface (NI).

(D) Rights of The Telephone Company

The Telephone Company will not provision OC-192 Dedicated SONET Ring Service if it has reasonably determined that (a) it is not technically feasible over existing facilities or (b) it will cause interference problems within The Telephone Company's network or other facilities.

(E) Responsibility of Customer

The customer is responsible for providing compatible customer provided equipment (CPE) to be used for connection to OC-192 Dedicated SONET Ring Service.

(N)

(This page filed under Transmittal No. 2847)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.2 Technical Specifications

Technical specifications for OC-192 Dedicated SONET Ring Service are listed in the following Telephone Company technical publications:

- (1) AM TR-TM0-000101 Ameritech Digital Service Transmission Parameters for Performance
- (2) AM TR-NIS-000111 Ameritech OC-3, OC-12, OC-48 and OC-192 Service Interface Specifications
- (3) TP 76839 SONET Transmission Requirements Performance and Interface Specification
- (4) SBC-TP-76412-000 Customer Interface Standards for 100 Mbps and Higher Excluding SONET Interfaces

30.3 Rate Regulations(A) Rate Elements(1) Nodes

The ring will provide connectivity to multiple customer designated locations (nodes). However, a ring must have a minimum of two nodes. At least one node must be a Telephone Company Central Office (CO) node. A maximum of 16 nodes including regenerators will be allowed per ring. The Telephone Company reserves the right to determine the order of the nodes on the ring⁽¹⁾.

When a customer premise node is located in the same building as a CO node, diversity between the two nodes may not be available.

If a customer collocates two customer premise nodes of the same speed, on the same dedicated ring, on the same premises, the additional node will be billed as shown in 30.4 following. This option does not guarantee diversity between these two collocated nodes and the rest of the ring.

The customer will be billed time and material as set forth in Section 13 preceding for any additional charges incurred by the Telephone Company in locating Telephone Company equipment at the customer premises.

(i) Re-Map Node

A Re-Map Node is a ring node that is pre-equipped and dedicated to customer traffic that is re-mapped/re-routed to it by the Telephone Company (upon notification by the customer of a service outage at another customer premises node on the same dedicated ring).

Re-Map is designed as a temporary service for disaster recovery purposes only. No "normal" customer traffic will be added/dropped at the Re-Map node unless the Re-Map service is activated.

- (1) A ring node providing an OC-48 connection to a collocation cage can be considered a customer premise node.

(This page filed under Transmittal No. 3135)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.3 Rate Regulations (Cont'd)(A) Rate Elements (Cont'd)(2) Add/Drop Capability

This provides the capability to add/drop lower speed channels from an OC-192 Dedicated Ring node location via OC-48 or OC-12 ports. OC-192 Add/Drop Capability at an OC-192 Dedicated SONET Ring Service node location will support various combination of service traffic not to exceed 192 STS-1 equivalents, contingent upon limitations of drop port capacity.

(3) Ports

Ports provide access to the ring and to lower speed channels (DS3, EC-1, OC-3, OC-3c, OC-12, OC-12c, OC-48, OC-48c, OC-192, 100 Mbps (STS-1) Ethernet, 100 Mbps (STS-3c) Ethernet, 1 Gbps (STS-1) Ethernet, 1 Gbps (STS-3c) Ethernet, 1 Gbps (STS-12c) Ethernet and 1 Gbps (STS-24c) Ethernet between nodes. Lower speed channels are accessible at nodes via port terminations.

(N)

Ethernet over SONET allows the efficient transport of Ethernet frames using SONET. Ethernet ports will be available in bandwidths up to the Ethernet interface of 100 Mbps or 1 Gbps on SONET Ring Services as set forth in the respective tariffs. As SONET bandwidths will be preset, the customer will be unable to transmit data (including any bursts) beyond these preset SONET bandwidths. Interfaces of 100 Mbps Ethernet or 1 Gbps Ethernet are available only to customers with Next Generation SONET equipment. Access into the Telephone Company's Ethernet ports must conform to industry standards and specifications as described in technical publication SBC-TP-76412-000.

Accepted interfaces are as follows:

	OC-192 Node
DS1 Ports	x(Max.84/OC-3Port)
DS3 Ports	x(Max.192/Node)
EC-1 Ports	x(Max.192/Node)
OC-3, OC-3c Ports	64
OC-12, OC-12c Ports	16
OC-48, OC-48c Ports	4
OC-192 Ports ⁽¹⁾	x(Max.1/Node)
100 Mbps (STS-1) Ethernet Ports	48
100 Mbps (STS-3c) Ethernet Ports	16
1 Gbps (STS-1) Ethernet Ports	32
1 Gbps (STS-3c) Ethernet Ports	16
1 Gbps (STS-12c) Ethernet Ports	2
1 Gbps (STS-24c) Ethernet Ports	2

(N)

(N)

(N)

(T)

(T)

(T)

(C)

(T)

(T)

OC-3, OC-3c, OC-12, OC-12c, OC-48 and OC-48c may be ordered at CO nodes. Both are available for Service-to-Service Through Connect with Broadband Circuit Service (BCS)*. OCN Point-to-Point Service is set forth in Section 40.

(1) OC-192 and OC-192c ports support both OC-192 and OC-192 bandwidths.

(N)

*This option is limited to existing customers at existing locations as of January 11, 2002.

(This page filed under Transmittal No. 3135)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.3 Rate Regulations (Cont'd)(A) Rate Elements (Cont'd)(4) Mileage

Mileage is charged as specified in 7.2.1, preceding. Fractions of a mile are rounded up to the whole mile for rate calculations. A one-mile minimum will be billed between nodes. A two-node ring configuration has a two-mile minimum, one mile from the wire center node to the customer premises node, and one mile from the customer premises node to the wire center node.

(5) Ring Regenerator

Regenerators provide essential detection and retransmission of the SONET Optical 9.953 Gbps signal between nodes. Regenerators will only be provided as required by the Telephone Company when actual fiber facility distances between nodes exceed inter-nodal design limits. Regenerators will be located exclusively in Telephone Company COs and do not allow ports to access customer service connections.

(6) Ethernet Over SONET (EoS)

Effective September 5, 2003, new orders for OC-192 Dedicated SONET Ring Service with the EoS enhancement will be served by different equipment than the equipment used for customers who placed OC-192 Dedicated SONET Ring Service orders that were completed prior to September 5, 2003. Customers subscribing to OC-192 Dedicated SONET Ring Service prior to September 5, 2003 requesting a change to the new equipment will incur early termination charges for their existing service. Disconnect of the existing OC-192 Dedicated SONET Ring Service and placement of an order for new OC-192 Dedicated SONET Ring Service with the EoS enhancement is required. The monthly rates for the new service(s) shall be those rates in effect at the time the new service(s) is installed.

(6) Electrical Connection - Level 1 (EC-1)

EC-1 is an electrical interface that can transport up to 51.84 Mb of bandwidth in a concatenated format. The EC-1 port is available on an OC-3, OC-12, OC-48 and OC-192 ring. For the above connection capacity charts, the quantity of EC-1 ports is equivalent to the connection capacity of a DS-3.

(N)
|
(N)

(This page filed under Transmittal No. 3135)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.3 Rate Regulations (Cont'd)(B) Dedicated Ring Connection Capacity

Maximum transport capacity of OC-192 Dedicated Ring Service is characterized by the total quantity of individual port-to-port connections allowed between all nodes on the ring.

For OC-192 Dedicated SONET Ring Service, the maximum ring capacity between adjacent nodes is not to exceed 96 STS-1 equivalents.

OC-192 Dedicated SONET Ring Service will provide capability for node-to-node connection of STS-1 or STS-3C channels using OC-3, OC-3c, OC-12, OC-12c, OC-48, OC-48c, 100 Mbps Ethernet and 1 Gbps Ethernet ports on the OC-192 ring.

(N)

OC-192 Dedicated SONET Ring Service will provide capability for node-to-node connections of STS-12C channels using OC-12, OC-12c, OC-48, OC-48c or 1 Gbps Ethernet ports on the OC-192 ring.

(N)

OC-192 Dedicated SONET Ring Service will provide capability for node-to-node connections of STS-48C channels using OC-48/48c ports on the OC-192 ring.

(N)

(This page filed under Transmittal No. 3120)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)

(N)

30.3 Rate Regulations (Cont'd)(C) Term Pricing Plan(1) General Description

OC-192 Dedicated Rings are available for either three or five year Term Pricing Plan (TPP) periods. Monthly recurring charges apply for the nodes, ports and mileage.

(2) Nonrecurring Charges

Nonrecurring Charges, including the Administrative Charge as set forth in 30.4 following, will apply for those arrangements ordered under the OC-192 Ring TPP. The Access Order Charge does not apply.

(3) Rate Flow Through

Any decreases in recurring tariff rates will be passed on to customers who participate in the TPP. The Telephone Company will notify customers participating in the TPP when monthly rates are decreased.

Should the Telephone Company increase its rates during the TPP period, the customer will pay the increased rates as long as the increase does not exceed the original tariffed rate in effect at the time the customer established service under the TPP.

(4) Adding Nodes to the Ring

If a node is added after the initial installation of the dedicated ring, the new node will carry the same TPP rate as the initial ring and be co-terminus with that TPP. However, if a node is added during the last 12 months of a TPP, the customer will be billed the initial node rate for a minimum period of 12 months. All applicable Nonrecurring Charges as set forth in Section 30.4 following will apply.

(5) TPP Renegotiation

The customer may choose to terminate an existing TPP at any time prior to the end of the three or five year period and negotiate a new TPP without termination liability provided the new TPP meets the following requirements:

(a) The minimum period for the new TPP must be greater than the remaining period currently in effect and

(b) The renegotiated TPP will be based on the current rates.

(This page filed under Transmittal No. 2847)

(N)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)

(N)

30.3 Rate Regulations (Cont'd)(C) Term Pricing Plan (Cont'd)(5) TPP Renegotiation (Cont'd)

When the customer converts to a new TPP, actual time in service for the original TPP will be applied. However, no credits or refunds will apply for the billing of actual time in service for the previous TPP.

(6) Renewal

The customer must provide the Telephone Company with a written notice of intent to renew a TPP no later than 60 days prior to its expiration.

The customer will continue to be billed at the current TPP rates.

If the customer does not renew the TPP, or does not notify the Telephone Company of its intent to renew the TPP, the customer's service will convert to the Monthly Extension rate as set forth in 30.4 following until the customer cancels or renews the service with a new TPP term. Monthly Extension Rates are not available to new subscriptions.

(N)

(This page filed under Transmittal No. 2847)

Issued: November 1, 2000

Effective: November 2, 2000

One Bell Plaza, Dallas, Texas 75202

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.3 Rate Regulations (Cont'd)(C) Term Pricing Plan (Cont'd)(7) Termination of Service

If a customer cancels a service order or terminates services before the completion of the term for any reason whatsoever other than a service interruption, the customer agrees to pay to the Telephone Company termination liability charges, which are defined below. These charges shall become due and owing as of the effective date of the cancellation or termination and are payable within 30 days of the invoice date, subject to interest penalty on the unpaid balance. (x)

Customer's termination liability for cancellation of service shall be equal to: (x)

- (a) All waived and/or unpaid nonrecurring charges, plus;
- (b) 50% of all recurring charges for the balance of the customer's term.

(D) Moves(1) Moves within a Customer's Premises

A move involves a change in the physical location of the Point of Termination on the customer's premises. Such moves will be treated as an extension of OC-192 Ring facilities. Extension of OC-192 Ring facilities will be provided, at the customer's request, on a time-sensitive charge basis. The labor rates that apply are set forth in Section 13 preceding (Rates and Charges). There will be no change in the TPP term requirements.

x Issued under authority of Special Permission No. 02-043 of the F.C.C. in order to restore currently effective provisions and to withdraw material filed under Transmittal No. 2881 without becoming effective.

(This page filed under Transmittal No. 2885)

Issued: March 20, 2002

Effective: March 21, 2002

One Bell Plaza, Dallas, Texas 75202

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.3 Rate Regulations (Cont'd)(D) Moves (Cont'd)(2) Moves of OC-192 Dedicated Ring Nodes

Moves of OC-192 Ring nodes will be provided, at the customer's request, on a time-sensitive charge basis. The charge will not exceed the Nonrecurring Charge for subsequent installation, as specified in Section 30.4(A), for the specific OC-192 Ring node being modified. The labor rates that apply are set forth in Section 13 preceding (Rates and Charges). Where facilities are not available, Special Construction charges may apply. No change in billing period is required. Termination charges will not apply to moves of OC-192 Ring nodes.

(E) Upgrade to OC-192 Dedicated SONET Ring Service from lower speed services

Customers with three or five year TPPs may at any time upgrade from OC-48 to OC-192 Dedicated SONET Ring Service without incurring the Termination Liability charge, providing the following criteria are met:

- The customer subscribes to a Term Pricing Plan period that is equal to, or greater than 36 months;
- The expiration date for the new Term Pricing Plan period is beyond the end of the original Term Pricing Plan period;
- No lapse in service occurs;
- Nonrecurring Charges will apply, when applicable;
- The monthly rates for the new service(s) will be those rates in effect at the time the new service(s) is/are installed;
- The new service is provided between the same customer locations and with the same customer of record as the disconnected service;
- The original location of all nodes must be included in the new service;
- Billed recurring revenue for each month of the first eighteen months of the new service is equal to or greater than the billed recurring revenue for the last month of the service(s) being converted;
- Customer agrees not to convert the new service term pricing plan to a pricing plan with a lower rate for the period of eighteen months after the conversion; and
- Spare facilities and equipment must be available or a nonrecurring upfront payment, which is a Special Construction Charge, may apply.

(T)

(N)

(N)

(C)

|

(C)

(N)

(N)

(N)

(F) Migration onto OC-192 SONET Ring

Billing for the OC-192 Dedicated SONET Ring service will commence upon service order completion for all rate elements. Billing for the existing OC-48 Ring service will continue until the migration of all circuit services on to the new OC-192 Ring is complete at which time the OC-48 Ring service may be disconnected.

(T)

(T)

(N)

|

(N)

(This page filed under Transmittal No. 2871)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.3 Rate Regulations (Cont'd)(G) Shared Network Arrangement⁽¹⁾

(C)

Shared Network Arrangement is a service offering that enables a customer ("Service User") to connect subtending services to an OC-192 Dedicated SONET Ring service of another customer (the "Host Subscriber"), with the Telephone Company maintaining separate billing for each. Each customer will be billed for those rate elements associated with their own portion of the service configuration. The Host Subscriber will be responsible for all OC-192 Dedicated SONET Ring Service rate elements, for example, node, ports and mileage, etc. Under no circumstances will the rates or charges for individual rate elements be split.

This offering is limited to service configurations where a Service User orders a subtending service dropped from a Host Subscriber's OC-192 Ring wire center node. Under Shared Network Arrangement, the Telephone Company may share record information with the Host Subscriber pertaining to the services of other users of the shared network. Such disclosure will be under the sole discretion of the Telephone Company and is necessary to perform billing reconciliation and/or other functions required in connection with maintaining account records.

(H) Shared Use

Shared Use occurs when Switched Access and Special Access services are provided over the same analog or digital high capacity facility or SONET based service through a common interface. The regulations governing the provision of Shared Use are set forth in 6.8.12, preceding.

While Shared Use of SONET facilities (i.e., OC-192 Dedicated SONET Ring Service) for Switched Access Transport is permitted, the SONET Special Access facilities continue to be rated as Special Access.

(1) Effective 05/26/06, this regulation is limited to existing customers. For new customers purchasing Shared Network Arrangement, terms and conditions set forth in Section 5.2.2 (Z), will apply.

(N)
(N)
(N)

(This page filed under Transmittal No. 3131)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.3 Rate Regulations (Cont'd)(I) Optical-to-Electrical Add/Drop Capability

(T)

1. The Optical-to-Electrical DS-1 allows an electrical DS-1 to be derived from an optical OC-192 ring by using this capability to add/drop the electrical DS-1 from an OC-3.

(N)

(N)

(N)

Effective 06/10/06, DS-1 Optical-to-Electrical Add/Drop Capability will be available from an optical OC-192 shelf.

The Optical-to-Electrical DS-1 Add/Drop Capability charge is applied when the 29th DS-1 port is required per OC-48 or OC-192 node. Additional charges will apply per each subsequent increment of 84 DS-1 ports.

(N)

(N)

2. The Optical-to-Electrical DS-3 Add/Drop Capability allows an electrical DS3 to be derived from an optical OC-3, OC-12, OC-48 or OC-192 shelf. The manner in which a DS3 is dropped will be designed based on forecast and equipment hierarchy.

(T)

For OC-192 SONET Rings established prior to 03/24/05, when electrical drops are required, the Optical-to-Electrical Add/Drop Capability charge is applied in addition to the Add/Drop Capability charge as described in Section 30.3(A)(2).

For OC-192 SONET Rings established after 03/24/05, the Optical-to-Electrical Add/Drop Capability charge is applied only once and only when the 25th DS-3 port is applied per node. Customers may upgrade their ring provided new TPP is equal to or greater than their existing TPP and the new MRC revenue is equal to or greater than their existing MRC revenue.

(This page filed under Transmittal No. 3168)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.3 Rate Regulations (Cont'd)

(J) Upgrade to Next Generation SONET equipment (required for Ethernet ports)

Customers with three or five-year OPPs may at any time upgrade to Next Generation equipment without incurring Termination Liability charges, providing the following criteria are met:

- The customer subscribes to a Term Plan period that is equal to, or greater than thirty-six months;
- The expiration date for the new Term Pricing Plan period is beyond the end of the original Optional Payment Plan period;
- No lapse in service occurs;
- Nonrecurring charges will apply, when applicable;
- The monthly rates for the new service(s) will be those rates in effect at the time the new service(s) is/are installed;
- The new service is provided between the same customer locations and with the same customer of record as the disconnected service;
- The original location of all nodes must be included in the new service.
- Billed recurring revenue for each month of the first eighteen months of the new service is equal to or greater than the billed recurring revenue for the last month of the service(s) being converted.

(K) Re-Map Service

Re-Map Service is provided in conjunction with Dedicated SONET Ring Service and allows for a pre-defined set of services to be re-routed by the Telephone Company from one customer premises node to another customer premises node (defined as a "Re-Map node") in the event of a customer premises disaster. Re-Map service will be tested at initial installation and once each year thereafter. Additional testing can be requested and will be charged on a per test basis. Activation upon customer request in the event of an emergency will be charged on a per occurrence basis.

Once the customer notifies the Telephone Company that they are ready to receive signals to the Re-Map node site, the Telephone Company will Re-Map up to 50 circuits within the initial hours and 20 circuits every hour thereafter. The Emergency Activation Nonrecurring Charge will not be applied if the first 50 circuits are not Re-Mapped within 4 hours due to a Telephone Company-caused delay.

(N)

(N)

(This page filed under Transmittal No. 3135)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.3 Rate Regulations (Cont'd)(K) Re-Map Service (Cont'd)

Re-Map testing and activation for OC-192 service requires a minimum of one DS1 (VT1.5), or 1 DS3 (STS-1) between one customer premises node and the Re-Map node. Re-Map testing or activation for OC-12 or OC-48 service requires a minimum incremental group from 1 to 28 DS1s or one DS3 (equals one STS-1) between one customer premises node and the Re-Map node.

The emergency Re-Map activation configuration will be maintained for up to 30 days. After 30 days, if the customer wishes to maintain the emergency configuration, the Emergency Activation Nonrecurring Charge will be applied once for each 30 day additional period.

Re-Map Service is available on Self-Healing Uni-Directional Path Switched Rings (UPSR) only.

(L) STS-1 Service

The STS-1 circuit allows the efficient transport of up to 51.84 Mbps of bandwidth across Dedicated SONET Ring utilizing EC-1 (Electrical Connection - Level 1) ports on the dedicated service. While the EC-1 port is comparable to the DS-3 port as far as the connection capacity per STS, the STS-1 circuit utilizes the entire bandwidth of the STS (51.84 Mbps) while the DS-3 uses 44.76 Mbps of the STS. The STS-1 circuit is available via EC-1 ports on an OC-192 ring.

(N)

(N)

(This page filed under Transmittal No. 3168)

Issued: October 2, 2006

Effective: October 17, 2006

Four AT&T Plaza, Dallas, Texas 75202

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.4 Rates and Charges(A) Nodes

Description	USOC	3 year	5 Year	Monthly Extension
- Customer Premises				
First	GP5AX	\$19,800.00	\$16,000.00	\$30,000.00
First Re-Map	RNFAX	19,800.00	16,000.00	33,000.00
Additional	GP5AA	17,800.00	14,200.00	26,500.00
Additional Re-Map	RNFAA	17,800.00	14,200.00	29,475.00
- Central Office	GC5AX	17,800.00	14,200.00	26,500.00

Description	USOC	Nonrecurring Charge
Nonrecurring charges for subsequent installation		
- Per Node		
Customer Premises	NRBS7	\$400.00
Customer Premises Re-Map	NRBS7	400.00
Central Office	NRBSV	325.00

(B) Add/Drop Capability

Description	USOC	3 year	5 Year	Monthly Extension
Per Arrangement				
- (per node) ⁽¹⁾ not to exceed any configurable combination of ports beyond 192 STS-1 equivalents	MXRGX	\$5,000.00	\$4,000.00	\$7,000.00
- Re-Map ⁽²⁾	M8RGX	\$4,500.00	3,600.00	\$7,000.00

(C) Ports

Description	USOC	3 year	5 Year	Monthly Extension
- Per Port				
DS1	S9QWX	50.00	45.00	65.00
DS3	S9QGX	120.00	110.00	150.00
DS3 w/Transmux ⁽²⁾	S4NGX	250.00	200.00	300.00
EC-1	S9TZX	120.00	110.00	150.00
OC-3, OC-3c	S9NEX/S9N++	135.00	120.00	225.00
OC-12, OC-12c	S9NGX/S9N++	325.00	300.00	600.00
OC-48, OC-48c	S9JX/S9N++	825.00	760.00	1350.00
OC-192 at OC-192 Node	S9T4X	3300.00	3000.00	5700.00
100 Mbps Ethernet (STS-1) at OC-192*	S9TNX	145.00	130.00	225.00
100 Mbps Ethernet (STS-3c) at OC-192*	S9TOX	180.00	160.00	280.00
1 Gbps Ethernet (STS-1) at OC-192*	S9TPX	250.00	200.00	350.00
1 Gbps Ethernet (STS-3c) at OC-192 node*	S9TQX	250.00	200.00	350.00
1 Gbps Ethernet (STS-12c) at OC-192 node*	S9TRX	600.00	500.00	875.00
1 Gbps Ethernet (STS-24c) at OC-192 node*	S9TSX	900.00	850.00	1500.00

(1) The OC-192 Add/Drop Capability charge is applied to all nodes, excluding Regenerators.

(2) Available for rings established on or after 10/17/06.

* Effective September 5, 2003, new orders for OC-192 Dedicated SONET Ring Service with the EoS enhancement will be served by different equipment. Disconnect of the existing OC-192 Dedicated SONET Ring Service and placement of an order for new OC-192 Dedicated SONET Ring Service with the EoS enhancement is required. Refer to Section 30.3(A)(6) for details.

(This page filed under Transmittal No. 3168)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.4 Rates and Charges (Cont'd)(C) Ports (Cont'd)

Description	USOC	36 Months	60 Months	Monthly Extension	
- Per port (Re-Map) Per DS1 Re-Map Block (consists of 28 DS1 ports) at OC-192 Ring	RN76X	\$1400.00	\$1260.00	\$1820.00	
Per DS3 Re-Map Block (consists of 3 DS3 ports at OC-192 Ring	RN77X	360.00	330.00	400.00	
Per DS3 Re-Map Port at OC-192 Ring	RN71X	120.00	110.00	150.00	
Per DS3 Transmux Re-Map ⁽¹⁾	RN7TX	250.00	200.00	300.00	(N)
Per EC-1 Re-Map Port at OC-192 Ring	S4NMX	120.00	110.00	150.00	
Per OC-3 Re-Map Port at OC-192 Ring	RN72X	150.00	135.00	190.00	
Per OC-12 Re-Map Port at OC-192 Ring	RN73X	375.00	360.00	475.00	
Per OC-48 Re-Map Port at OC-192 Ring	RN74X	825.00	700.00	1425.00	

Description	USOC	Nonrecurring Charge	
Nonrecurring charges for subsequent installation			
- Per port type			
DS1	NRBSY	\$350.00	
DS3	NRBSX	385.00	
DS3 w/Transmux ⁽¹⁾	NRBSX	385.00	(N)
EC-1	NRBSX	385.00	
OC-3, OC-3c	NRBSW	400.00	
OC-12, OC-12c	NRBSZ	400.00	
OC-48, OC-48c	NRBN9	425.00	
OC-192	NRBN2	850.00	
100 Mbps Ethernet (STS-1) at OC-192*	NRM63	385.00	
100 Mbps Ethernet (STS-3c) at OC-192 node*	NRM64	385.00	
1 Gbps Ethernet (STS-1) at OC-192 node*	NRM65	425.00	
1 Gbps Ethernet (STS-3c) at OC-192 node*	NRM66	425.00	
1 Gbps Ethernet (STS-12c) at OC-192 node*	NRM67	425.00	

⁽¹⁾ Available for rings established on or after 10/17/06.

* Effective September 5, 2003, new orders for OC-192 Dedicated SONET Ring Service with the EoS enhancement will be served by different equipment. Disconnect of the existing OC-192 Dedicated SONET Ring Service and placement of an order for new OC-192 Dedicated SONET Ring Service with the EoS enhancement is required. Refer to Section 30.3(A)(6) for details.

(This page filed under Transmittal No. 3168)

Issued: October 2, 2006

Effective: October 17, 2006

Four AT&T Plaza, Dallas, Texas 75202

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.4 Rates and Charges (Cont'd)(D) Mileage

Description	USOC	3 Year	5 Year	Monthly Extension
Per mile between nodes ⁽²⁾	1YAZX/IYA++	\$260.00	\$210.00	\$330.00

(E) Ring Regenerator

	USOC	3 Year	5 Year	Monthly Extension
Each (as required)	RGY	\$9,250.00	\$7,400.00	\$13,875.00

Description	USOC	Nonrecurring Charge
Nonrecurring charges for subsequent installation of Regenerator		
- Each (as required)	NRBS5	\$270.00

(F) Shared Network Arrangement

Description	USOC	Nonrecurring Charge
Processing Charge Per Service Order	NRMCL	\$30.00

(G) Installation and Administrative Charges

Description	USOC	Nonrecurring Charge
STS-1 Service	ORCMX	\$60.00
Administrative Charge per Service Order	ORCMX	60.00
Design and Central Office Connection Charge, per Initial Ring	NRMCK	2,250.00 ⁽¹⁾

(1) Per Ring Charge for Dedicated Ring Service is applied once per original ring installed.

(2) A two-node ring configuration has a two-mile minimum, one mile from the CO node to the customer premise node, and one mile from the customer premise node to the CO node.

(This page filed under Transmittal No. 3168)

Issued: October 2, 2006

Effective: October 17, 2006

Four AT&T Plaza, Dallas, Texas 75202

(N)

ACCESS SERVICE

30. OC-192 Dedicated SONET Ring Service (Cont'd)30.4 Rates and Charges (Cont'd)(G) Installation and Administrative Charges (Cont'd)

Description	USOC	Nonrecurring Charge
Re-Map Service		
Initial Service Script Establishment/ Test Charge	NRMR1	\$5,500.00
Subsequent Script Activity Charge	NRMR3	3,200.00
Scheduled Test Charge	NRMR5	4,200.00
Emergency Re-Map Activation (per request)	NRMR7	5,000.00

(H) Optical-to-Electrical Add/Drop Capability

Description	USOC	36 Months	60 Months	Monthly Extension
Per Arrangement ⁽¹⁾				
- (per node) not to exceed any configurable combination of ports beyond 192 STS-1 equivalents	MXJGX	\$2,500.00	\$2,000.00	\$3,500.00
- Re-Map ⁽²⁾	M6JGX	\$2,500.00	\$2,000.00	\$3,500.00
Per Optical to Electrical DS-3 Add/Drop Capability				
Per OC-3 to DS-1 Add/Drop ⁽³⁾	MXJDX	875.00	700.00	1,050.00
Re-Map Per OC-3 to DS-1 Add/Drop ⁽³⁾	M8RDX	875.00	700.00	1,050.00

(N)

(N)

Description	USOC	Nonrecurring Charge
Subsequent Installation Per OC-3 to DS-1 Add/Drop	NRBS6	\$490.00
Subsequent Installation Optical/Electrical of DS3 Add/Drop	NRBS8	490.00

(N)

(N)

(N)

(1) When electrical drops are required, the Optical-to-Electrical Add/Drop Capability charge is applied in addition to the Add/Drop Capability charge set forth in Section 30.4(B), preceding.

(2) Available for rings established on or after 10/17/06.

(3) An OC-3 port charge is needed with each Optical-to-Electrical Add/Drop Capability - Per OC-3 to DS-1 Add/Drop.

(N)

(N)

(N)

(This page filed under Transmittal No. 3168)

Issued: October 2, 2006

Effective: October 17, 2006

Four AT&T Plaza, Dallas, Texas 75202

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

(T)

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

(T)

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

(T)

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

(T)

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

(T)

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

(T)

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

(T)

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

(T)

ACCESS SERVICE

(D)

(D)

(This page filed under Transmittal No. 2792)

Issued: November 12, 1999

Effective: November 29, 1999

One Bell Plaza, Dallas, Texas 75202

(T)